


M415-14Ever1.0



Product Description

1. Working Voltage: DC3V (2×AAA battery)
2. Static Current: ≤5uA
3. Alarm Current: ≤35mA
4. Detecting Distance: > 15mm
5. Networking: ZigBee Ad-Hoc Networking
6. Wireless Networking Distance: ≥70m (in the open area)
7. Working Environment: -10°C ~ +50°C
8. Working Humidity: Maximum 95%RH
(No condensation)
9. Detector Dimension: 76×36.6×16.5 mm
10. Magnet Dimension: 76×13.9×16.5 mm

Technical parameters

Function Representation



A diagram illustrating the coin insertion step. A hand is shown inserting a coin into a coin slot on the side of the device. A callout bubble highlights the coin slot area.

- 5

- 6

Diagram illustrating the internal components of the device, including the Anti-tamper Button and Networking Button. A callout shows a hand pressing the button.

- ## LED indicator instruction of devices

Light	Status
Green Light	1.Flash quickly during connecting network. 2.Keep on for 2-3 seconds when networking succeed. 3.Flash quickly for 1 minute after networking fail.
	1.Flash once when power on. 2.Keep on 2-3 seconds after long press networking hole for 8 seconds to disconnect network.
Red light	1.When the alarm light 0.5 to 1 seconds or so.

8

Step 4




• Align sensor and magnet, the installation distance should be less than 15mm. (The magnet can be installed on both sides of the sensor)

- Align sensor and magnet, the installation distance should be less than 15mm. (The magnet can be installed on both sides of sensor)

9

Step 5




- Tear off the double-side tap, paste the device in the require area. Sensor should be installed in fixed area like door frame magnet can be installed in active area like door plank, the picture for reference only.

- Tear off the double-side tap, paste the device in the required area. Sensor should be installed in fixed area like door frame, magnet can be installed in active area like door plank, this picture for reference only.

1C

- 1.

Changing Battery



Statement
*Instruction is for reference only, please prevail in kind.
*Because of the updating of the technology, the final interpretation right owned by factory, if there are any inconformities when using this products under this instruction.

13